

QRN-410S


4Ch Network Video Recorder with built-in PoE Switch



Key Features

- Up to 4ch 8megapixel supported
- H.265, H.264, MJPEG codec supported
- 40Mbps network camera recording
- Plug & play by 4 PoE ports
- Max. 1HDD supported
- HDMI local monitor
- P2P service (QR code connect) support

Unit:mm (inch) **Dimensions**



		QRN-410S
DISPLAY		
	Inputs	Max.4ch
Network Camera	Resolution	CIF~8MP
Carriera	Protocols Local Display	Wisenet, ONVIF (Profile-S)
Live		[Local Monitor] 1/2H/2V/3V/4/Auto Sequence
	Multi-Channel Display Performance	[Web] 1/4/Auto Sequence [Local Monitor] 8MP (60fps)
DEDECOMANICE		5MP (90fps), 3MP (120fps), 2MP (120fps), 720p (120fps), D1 (120fps)
PERFORMANCE		Linux
Operating System	Compression	Linux H.265, H.264, MUPEG
	Recording Bandwidth	Max.40Mbps
Record	Resolution	CIF~8MP
	Type Event Trigger	Manual, Schedule (Continuous / Event), Event (Pre / Post)
	Event Trigger Event Action	Video Loss, Camera event (Sensor, MD, Video analytics, Defocus) e-Mail, PTZ Preset, Buzzer, Monitor Out
Search & Play	Playback Bandwidth	32Mbps (4ch simultaneously) Max. 3 Users (Local 1,Remote 3)
	Performance	Max. 3 Users (Local 1, Remoté 3)
	Mode	Date & Time (Calendar) / Event Log list / Text Search (POS) / ARB Search / Smart Search (Virtual Line w / direction, Enter / Exit) Max. 4ch (Local, Network)
	Simultaneous playback	Max. 4ch (Local, Network)
	Resolution	CIF ~ 8MP N/A (processed on Web/CMS)
	Fish-Eye Dewarping Playback Control	N/A (processed on Web / CMS) Fast / Slow Forward / Backward, Move one step Up / Down
<u></u>	Default Built-In	0~6TB
Storage	Internal	1 (Max.6TB)
Backup	File backup	BU/Exe (USB), JPG/AVI (Web, CMS)
Sensor	Function I/O	Multi channel (Upto 4ch) Play, Date-Time / Title display N/A
	Input	4 ch (network)
Audio	Compression	G.711, G.726, AAC (16 / 48KHz)
NETWORK	Audio Communication	2-Way
Protocol		TCP / IP, UDP / IP, RTP (UDP), RTP (TCP), RTSP, NTP, HTTP, DHCP (Server, Client), PPPGE, SMTP, ICMP, IGMP, ARP, DNS, DDNS, uPnP, HTTPS, SNMP, ONVIF (Profile-S),
DDNS		SUNAPI (Server, Client) Hanwha Security DDNS
Transmission Bandwidth		50Mbps
Max Remote Users		Search (3), Live Unicast (10), Multicast (20)
IP Version		IPv4/IPv6 User access Log, IP Filtering, 802.1x, Encryption
<u>Security</u> Language		English, French, German, Italian, Spanish, Russian, Turkish, Polish, Dutch, Swedish,
	GUI	Czech, Portuguese, Danish, Rumanian, Serbian, Croatian, Hungarian, Greek,
		Norwegian, Finnish, Korean, Chinese (Simplified), Japanese, Thai
	Web	Czech, Portuguese, Danish, Rumanian, Serbian, Croatian, Hungarian, Greek,
		Norwegian, Finnish, Korean, Chinese (Simplified), Japanese, Thai
OS V		Windows 7, 8, 10, Mac US X 10.9, 10.10, 10.11 Plug-in free web viewer: Google Chrome 47, MS Edge 20
Web Browser		Plug-in Webviewer: MS Explorer 11, Apple Safari 9 (Mac OS X only)
Viewer	Type	English, French', German, Italian, Spanish, Russian, Turkish, Polish, Dutch, Swedish, Czech, Portuguese, Danish, Rumanian, Serbian, Croatian, Hungarian, Greek, Norwegian, Finnish, Korean, Chinese (Simplified), Japanese, Thai English, French, German, Italian, Spanish, Russian, Turkish, Polish, Dutch, Swedish, Czech, Portuguese, Danish, Rumanian, Serbian, Croatian, Hungarian, Greek, Norwegian, Finnish, Korean, Chinese (Simplified), Japanese, Thai Windows 7, 8, 10, Mac OS X 10,9, 10.10, 10.11 Plug-in free web viewer: Google Chrome 47, MS Edge 20 Plug-in Webviewer: SMS Explorer 11, Apple Safari 9 (Mac OS X only) SSM, Webviewer, Smart Viewer, Wisenet Mobile Support SDK/CGI (SUNAPI)
Software FUNCTIONS	CMS Support	Support SDR/ CGI (SUNAPI)
TORCHORS	Register	PnP, Manual
C C-+		IP address, Add profile edit, Bitrate, Compression, GOP, Quality, Camera MD setup
Camera Setup	Setup Items	Camera video setup (Simple focus, Brightness / Contrast, Flip / Mirror, IRIS, WDR, D&N, SSNR, Shutter, SSDR, DIS), Fisheye Dewarping setup, Hallway View Setup,
		Camera Webpage
Camera Control	PoE	Camera Webpage Monitor PoE Power consumption , On / Off Control for each PoE camera , Remote Reset for each PoE camera
		Setup Wizard (Date / Time, Network, Auto Camera Configuration)
Easy Configuration		P2P (OR code)
ARB		Yes Via C.I.I. Washingwar 355 procest
PTZ	Control Support Model	Via GUI, Webviewer, 255 preset iPhone, Android
Smart phone System Control	Protocol Support	RTP,RTSP,HTTP,CGI (SUNAPI)
	Control	Live (4ch): Multi-Profile Support, Plavback (4ch), Event push
	Max. Remote Users	Search (3), Live Unicast (10), Multicast (20) Mouse, Web
INDICATOR/IN	TERFACE	
Front	Indicator	LED (Status indicator): 3ea
Connectors	VGA	Power Status 1, LAN 1, Record 1
	HDMI	1 EA (3840 x 2160, 1920x1080, 1280x720)
	Audio	I N/A
	Ethernet	4EA (PoE, 100Mbps) 1EA (WAN, 100Mbps) - WAN : Uplink to CMS
	Alarm	N/A
	USB Ext Storage	Front 1EA (USB2.0), Rear 1 (USB3.0)
	Ext. Storage Serial	WA WA
	Reset	Switch (1EA)
CVCTELA	Power Cord	Included
SYSTEM Log Log List Max. 20000 (System Log, Event Log each)		
ENVIRONMENTAL INITIAL INITIALIA INITIAL INITIAL INITIALIA INITIAL INIT		Thian, 20000 (Dystern Eog., Event Eog Edet)
Operating Temperature / Humidity		+0°C to +40°C (+32°F to +104°F) 20%~85% RH
		20%~85%RH
ELECTRICAL Power Input		5/VDC /1 3A
Power Input Power Consumption		54V DC / 1.2A Max. 47W (1HDD, PoE on), Max. 7.4W (1HDD, PoE off)
PoE Budget 1		Max.25W
MECHANICAL Color (Massaria) Disale (Adapta)		
Color/Material Dimension (WxHxD)		Black/Metal W300.0 x H47.1 x D208.4 mm (1U) (11.81" x 1.85" x 8.20")
Weight		0.99Kg (2.18 lb) (without HDD)

^{*}The lastest product information / specification can be found at hanwha-security.com
*Design and specifications are subject to change without notice.
*Wisenet is the proprietary brand of **Hanwha Techwin**, formerly known as Samsung Techwin.